

3) Wire receptacle with 7-way cable per drawing and chart below.

4) NOTE: Truck chassis will be wired to match this diagram.

<u>Conductor ID</u>	<u>Wire Color</u>	<u>Lamp &amp; Signal Circuits</u>
1 WHT	White	Ground return to towing vehicle*
6 BLK	Black	Clearance, side mark, ident lamps
5 YEL	Yellow	Left-turn signal & stop
4 RED	Red	Back-up lights
3 GRN	Green	Right-turn signal & stop
2 BRN	Brown	Tail lights
7 BLU	Blue	Auxiliary (Dome lights)

\* If required

